



# **LS 600D Pro**

DMX Profile Specification

Controller Firmware v1.0

**Mode: Lighting & Effect 8-bit**

Channel	Value	Percent	Function	
1	0 - 255	0 - 100	<b>Intensity</b>	0 - 100%
2	0 - 127 128 - 255	0 - 49 50 - 100	<b>Lighting / Effects</b>	Lighting Effects
3	0 - 19 20 - 39 40 - 59 60 - 79 80 - 99 100 - 119 120 - 139 140 - 159 160 - 255	0 - 7 8 - 15 16 - 23 24 - 31 32 - 39 40 - 47 48 - 55 56 - 63 64 - 100	<b>Effects</b>	Paparazzi Fireworks Faulty bulb Lightning TV Pulsing Strobe Explosion Reserved
4	0 - 19 20 - 39 40 - 59 60 - 79 80 - 99 100 - 119 120 - 139 140 - 159 160 - 179 180 - 199 200 - 219 220 - 255	0 - 7 8 - 15 16 - 23 24 - 31 32 - 39 40 - 47 48 - 55 56 - 63 64 - 71 72 - 79 80 - 87 88 - 100	<b>Frequency</b>	1 2 3 4 5 6 7 8 9 10 Random Reserved
5	0 - 10 11 - 127 128 - 255	0 - 4 5 - 49 50 - 100	<b>Lightning</b>	Stop Trigger Loop
	0 - 10 11 - 127 128 - 255	0 - 4 5 - 49 50 - 100	<b>Explosion</b>	Stop Trigger Reserved